

We. BOOST

Wireless plug & play home theater system



Dolby Atmos home theater surround sound system
Wireless active satellite speakers and subwoofer
720 watts of total music power for immersive home cinema
3D surround sound and dual stereo mode with Dolby Atmos, Dolby Digital and PCM
Plug-and-play installation already fully pre-paired and pre-configured
HDMI eARC dongle for easy setup and compatibility with many modern TV sets
Bluetooth streaming, line in and center out for extended use cases

■●■Dolby Atmos







We. by LOEWE.

We. BOOST

Wireless plug & play home theater system



Home cinema set

We. BOOST subwoofer: $W \times H \times D = 23.9 \times 38.7 \times 23.9$ We. BOOST satellite: $W \times H \times D = 12.0 \times 20.1 \times 12.0$







Model	Article
BOOST	64720

Dolby Atmos home theater

Experience cinema-quality sound right in your living room with our Dolby Atmos home theater system. Feel every detail, from the quietest whisper to the loudest explosion, as sound moves around you in a stunning 3D space.

Wireless plug & play

Say goodbye to complicated setups! Our home theater system is pre-configured for plug-and-play convenience. Just connect with mains, and you're ready to immerse yourself in high-quality sound without the hassle.

Powerful 3D surround sound

Lift your audio experience to the next level with 3D surround sound and dual stereo mode. Whether it's movies, music, or gaming, you'll be fully immersed as sound surrounds you from every direction, creating an unforgettable entertainment experience.

Screen solutions



We. by LOEWE.

We. BOOST

Wireless plug & play home theater system

Technical data

We. by Loewe

We. BOOST

110.07 200110	
Audio (acoustic)	
Frequency range (ca. Hz) @ ±3 dB	sub: 43-120 & sat: 120-20.000
Max. sound pressure level (ca. dB SPL) @ 1m, pink noise, max. vol.	97
Orientation front / side / up / rear firing	•/•/•/•
Acoustic speaker concept	bass reflex
Channel configuration	4.1.2
Driver total amount	13
Driver active	4x 3,5" + 4x 1,5" + 4x 2" + 6,5" woofer
2-channel crossover	•
	<u>·</u>
Audio (electric)	00.00.000
Frequency range (ca. Hz) @ ±1 dB	20-20.000
Class-D amp	
Power (ca. watts sine / music)	sub: 120 / 240 & sat: 30 + 30 / 60 + 60
Total harmonic distortion ca. @ 1 watt /10 watts	< 0,2 % @ max. volume
Dynamic range / Signal to noise ratio (ca. dB)	sub: 73 dB, sat: 86 dB
Bass and treble control / night mode	
Distance adjustment (m)	_ •
Balance / gain adjustment (ca. dB)	_ •
Dual stereo mode	•
Dolby Audio / Digital / Digital Plus / Volume / Atmos / Atmos Music	•/•/•/•
Operation and apps	
Display technology	OLED (bi-directional BLE remote)
my Loewe app / smart apps (all: Android + iOS)	• / -
Software update (via USB / Internet)	• / -
Connectivity and Interfaces	
HDMI	•
HDCP 2.2 / HDMI-CEC / ARC / eARC	•/•/•/•
USB	•
Bluetooth	BLE (incl. bi-directional remote)
Analogue audio jack in (3,5 mm stereo)	• BEE (Inc. or directional official)
Center speaker out (2,5 mm mono)	
Tripod screw thread	• (M5)
Wall mount	•
	`
Network and formats	denotes 5.4
Bluetooth standard	dongle: 5.4
Bluetooth power (mW)	<10
Bluetooth frequency range	2400-2483,5 MHz
Bluetooth protocols	A2DP, AVCTP, AVDTP, AVRCP, HFP
Supported audio formats	PCM, Dolby True HD, Dolby Audio, Dolby Digital, Dolby Digital Plus, Dolby Atmos, Dolby Atmos Musi
Energy and environment	
Mains voltages AC	100-240V, 50/60 Hz
Power consumption standby mode (watts)	
Ambient temperature while in operation	0-45° C
Relative humidity (non-condensing)	20-90%
Dimensions	
Weight (ca. kg)	sub: 6,2 & sat: 1,5
W* x H x D (ca. cm)	sub: 23,9 x 38,7 x 23,9 & sat: 12,0 x 20,1 x 12,0
Scope of Delivery	
Remote control (incl. batteries)	Bluetooth (BLE) bi-directional, incl. OLED display
Manual / power cord	• / • [5]
Other cable	USB adapter (A > C), USB splitter (1x A > 2x C), HDMI extension
Others	2x wall mount
Optional accessories	Laborate Hamiltonia (O. / E. der Laborate in A. / E. L. d
Selection of recommended setup solutions and audio systems	Loewe stellar 42-65 dr+, Loewe inspire 48-65 dr+, Loewe callas 32-43
	We. SEE oled 48-65, We. SEE lcd 32-43, We. BEAM
Specials	Smart bi-directional remote control with Bluetooth Low Energy (BLE) and OLED matrix display.
	Optional individual tuning of the system: Distance of the speakers to the listening position and set-
	ting the volume level with noise signal. Display of the values on the remote control. Centre out for
	separate centre speaker. Dual stereo mode for better speech intelligibility.

^{• =} available, o = optional, — = not available

Technical changes, delivery options, errors and price changes reserved. All product and company names are trademarksTM or registered® trademarks of their respective owners. Their use does not imply any affiliation with or endorsement by these companies. Digital services and content (e.g., apps) and server platforms are provided by third parties. Available for download in the App Store. Observe the terms of use of the third party on the device. The provision, availability (including in certain territories), updating and termination of the provision of this digital content and services on the device are at the sole discretion of the third party. Some services may not be available to the time of purchase of this product. Internet access required. Separate (poid) subscriptions and/or membership required. Ultra HD and HDR availability subject to subscription plan, internet service, device features and content availability.